

850 Purchase Order

X12/V4010/850: 850 Purchase Order

Version: 1.1 Draft

Author: ScanSource

Publication:

Trading Partner:

Notes:

850 Purchase Order

Functional Group=PO

This Draft Standard for Trial Use contains the format and establishes the data contents of the Purchase Order Transaction Set (850) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to the placement of purchase orders for goods and services. This transaction set should not be used to convey purchase order changes or purchase order acknowledgment information.

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	ST	Transaction Set Header	M	1			Must use
020	BEG	Beginning Segment for Purchase Order	M	1			Must use
050	REF	Reference Identification	O	>1			Used
130	ITD	Terms of Sale/Deferred Terms of Sale	O	>1			Used
150	DTM	Date/Time Reference	O	10			Used
240	TD5	Carrier Details (Routing Sequence/Transit Time)	O	12			Used

<u>LOOP ID - N9</u>			<u>1000</u>				
295	N9	Reference Identification	O	1			Used
300	MSG	Message Text	O	1000			Used
<u>LOOP ID - N1</u>			<u>200</u>				
310	N1	Name	O	1			Used
320	N2	Additional Name Information	O	2			Used
330	N3	Address Information	O	2			Used
340	N4	Geographic Location	O	>1			Used
360	PER	Administrative Communications Contact	O	>1			Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<u>LOOP ID - PO1</u>					<u>100000</u>	<u>N2/010L</u>	
010	PO1	Baseline Item Data	M	1		N2/010	Must use
<u>LOOP ID - PID</u>					<u>1000</u>		
050	PID	Product/Item Description	O	1			Used
289	MSG	Message Text	O	>1			Used

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - CTT					1	N3/010L	
010	CTT	Transaction Totals	O	1		N3/010	Used
020	AMT	Monetary Amount	O	1		N3/020	Used
030	SE	Transaction Set Trailer	M	1			Must use

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	GE	Functional Group Trailer	M	1			Must use
	IEA	Interchange Control Trailer	M	1			Must use

Notes:

- 2/010L PO102 is required.
- 2/010 PO102 is required.
- 3/010L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.
- 3/010 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.
- 3/020 If AMT is used in the summary area, then AMT01 will = TT and AMT02 will indicate total transaction amount as calculated by the sender.

ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

User Option (Usage): Must use

To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	Authorization Information Qualifier	M	ID	2/2	Not used
Description: Code to identify the type of information in the Authorization Information						
All valid standard codes are used.						
ISA02	I02	Authorization Information	M	AN	10/10	Not used
Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)						
ISA03	I03	Security Information Qualifier	M	ID	2/2	Not used
Description: Code to identify the type of information in the Security Information						
All valid standard codes are used.						
ISA04	I04	Security Information	M	AN	10/10	Not used
Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)						
ISA05	I05	Interchange ID Qualifier	M	ID	2/2	Must use
Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified						
Code Name						
12 Phone (Telephone Companies)						
ISA06	I06	Interchange Sender ID	M	AN	15/15	Must use
Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element						
User Note 1: CATALYST: 8003905376						
PARACON: 8009981221						
SCANSOURCE: 8642882432						
SCANSOURCE SECURITY: 8009648994						
TEST: 8643298222						
ISA07	I05	Interchange ID Qualifier	M	ID	2/2	Must use
Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified						
All valid standard codes are used.						
ISA08	I07	Interchange Receiver ID	M	AN	15/15	Must use
Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a						

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
		receiving ID to route data to them				
ISA09	I08	Interchange Date	M	DT	6/6	Must use
		Description: Date of the interchange				
ISA10	I09	Interchange Time	M	TM	4/4	Must use
		Description: Time of the interchange				
ISA11	I10	Interchange Control Standards Identifier	M	ID	1/1	Must use
		Description: Code to identify the agency responsible for the control standard used by the message that is enclosed by the interchange header and trailer				
		All valid standard codes are used.				
ISA12	I11	Interchange Control Version Number	M	ID	5/5	Must use
		Description: Code specifying the version number of the interchange control segments				
		All valid standard codes are used.				
ISA13	I12	Interchange Control Number	M	N0	9/9	Must use
		Description: A control number assigned by the interchange sender				
ISA14	I13	Acknowledgment Requested	M	ID	1/1	Must use
		Description: Code sent by the sender to request an interchange acknowledgment (TA1)				
		All valid standard codes are used.				
ISA15	I14	Usage Indicator	M	ID	1/1	Must use
		Description: Code to indicate whether data enclosed by this interchange envelope is test, production or information				
		All valid standard codes are used.				
ISA16	I15	Component Element Separator	M		1/1	Must use
		Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator				

GS Functional Group Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

User Option (Usage): Must use

To indicate the beginning of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS01	479	Functional Identifier Code	M	ID	2/2	Must use
		Description: Code identifying a group of application related transaction sets				
		Code Name				
		PO Purchase Order (850)				
GS02	142	Application Sender's Code	M	AN	2/15	Must use
		Description: Code identifying party sending transmission; codes agreed to by trading partners				
		User Note 1: CATALYST: 8003905376 PARACON: 8009981221 SCANSOURCE: 8642882432 SCANSOURCE SECURITY: 8009648994 TEST: 8643298222				
GS03	124	Application Receiver's Code	M	AN	2/15	Must use
		Description: Code identifying party receiving transmission; codes agreed to by trading partners				
GS04	373	Date	M	DT	8/8	Must use
		Description: Date expressed as CCYYMMDD				
GS05	337	Time	M	TM	4/8	Must use
		Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)				
GS06	28	Group Control Number	M	N0	1/9	Must use
		Description: Assigned number originated and maintained by the sender				
GS07	455	Responsible Agency Code	M	ID	1/2	Must use
		Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480				
		All valid standard codes are used.				
GS08	480	Version / Release / Industry Identifier Code	M	AN	1/12	Must use
		Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade				

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
		association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed				
		<u>Code</u>	<u>Name</u>			
		004010	Draft Standards Approved for Publication by ASC X12 Procedures Review Board through October 1997			

Semantics:

1. GS04 is the group date.
2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

ST Transaction Set Header

Pos: 010	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use
		Description: Code uniquely identifying a Transaction Set All valid standard codes are used.				
ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

Semantics:

1. The transaction set identifier (ST01) used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).

BEG Beginning Segment for Purchase Order

Pos: 020	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 5

User Option (Usage): Must use

To indicate the beginning of the Purchase Order Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BEG01	353	Transaction Set Purpose Code	M	ID	2/2	Must use

Description: Code identifying purpose of transaction set

User Note 1: *Currently only 00:ORIGINAL is used.*

Code Name

00	Original
01	Cancellation
04	Change
05	Replace

BEG02	92	Purchase Order Type Code	M	ID	2/2	Must use
-------	----	---------------------------------	---	----	-----	----------

Description: Code specifying the type of Purchase Order

Code Name

DS	Dropship
NO	Not for Sale
SA	Stand-alone Order

BEG03	324	Purchase Order Number	M	AN	1/22	Must use
-------	-----	------------------------------	---	----	------	----------

Description: Identifying number for Purchase Order assigned by the orderer/purchaser

BEG04	328	Release Number	O	AN	1/30	Not used
-------	-----	-----------------------	---	----	------	----------

Description: Number identifying a release against a Purchase Order previously placed by the parties involved in the transaction

BEG05	373	Date	M	DT	8/8	Must use
-------	-----	-------------	---	----	-----	----------

Description: Date expressed as CCYYMMDD

Semantics:

1. BEG05 is the date assigned by the purchaser to purchase order.

REF Reference Identification

Pos: 050	Max: >1
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

To specify identifying information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
REF01	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

Code Name

VR Vendor ID Number

REF02	127	Reference Identification	X	AN	1/30	Used
-------	-----	--------------------------	---	----	------	------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

ITD Terms of Sale/Deferred Terms of Sale

Pos: 130	Max: >1
Heading - Optional	
Loop: N/A	Elements: 7

User Option (Usage): Used

To specify terms of sale

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ITD01	336	Terms Type Code	O	ID	2/2	Not used
		Description: Code identifying type of payment terms All valid standard codes are used.				
ITD02	333	Terms Basis Date Code	O	ID	1/2	Not used
		Description: Code identifying the beginning of the terms period All valid standard codes are used.				
ITD03	338	Terms Discount Percent	O	R	1/6	Used
		Description: Terms discount percentage, expressed as a percent, available to the purchaser if an invoice is paid on or before the Terms Discount Due Date				
ITD04	370	Terms Discount Due Date	X	DT	8/8	Used
		Description: Date payment is due if discount is to be earned expressed in format CCYYMMDD				
ITD05	351	Terms Discount Days Due	X	N0	1/3	Used
		Description: Number of days in the terms discount period by which payment is due if terms discount is earned				
ITD06	446	Terms Net Due Date	O	DT	8/8	Not used
		Description: Date when total invoice amount becomes due expressed in format CCYYMMDD				
ITD07	386	Terms Net Days	O	N0	1/3	Used
		Description: Number of days until total invoice amount is due (discount not applicable)				

Syntax Rules:

1. L03040513 - If ITD03 is present, then at least one of ITD04, ITD05 or ITD13 is required.
2. L08040513 - If ITD08 is present, then at least one of ITD04, ITD05 or ITD13 is required.
3. L091011 - If ITD09 is present, then at least one of ITD10 or ITD11 is required.

Semantics:

1. ITD15 is the percentage applied to a base amount used to determine a late payment charge.

Comments:

1. If the code in ITD01 is "04", then ITD07 or ITD09 is required and either ITD10 or ITD11 is required; if the code in ITD01 is "05", then ITD06 or ITD07 is required.

DTM Date/Time Reference

Pos: 150	Max: 10
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use
		Description: Code specifying type of date or time, or both date and time				
		Code Name				
		002				Delivery Requested
DTM02	373	Date	X	DT	8/8	Used
		Description: Date expressed as CCYYMMDD				

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

TD5 Carrier Details (Routing Sequence/Transit Time)

Pos: 240	Max: 12
Heading - Optional	
Loop: N/A	Elements: 3

User Option (Usage): Used

To specify the carrier and sequence of routing and provide transit time information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
TD501	133	Routing Sequence Code	O	ID	1/2	Not used
		Description: Code describing the relationship of a carrier to a specific shipment movement All valid standard codes are used.				
TD502	66	Identification Code Qualifier	X	ID	1/2	Used
		Description: Code designating the system/method of code structure used for Identification Code (67)				
		Code Name				
		ZZ Mutually Defined				
TD503	67	Identification Code	X	AN	2/80	Used
		Description: Code identifying a party or other code				

Syntax Rules:

1. R0204050612 - At least one of TD502, TD504, TD505, TD506 or TD512 is required.
2. C0203 - If TD502 is present, then TD503 is required.
3. C0708 - If TD507 is present, then TD508 is required.
4. C1011 - If TD510 is present, then TD511 is required.
5. C1312 - If TD513 is present, then TD512 is required.
6. C1413 - If TD514 is present, then TD513 is required.
7. C1512 - If TD515 is present, then TD512 is required.

Semantics:

1. TD515 is the country where the service is to be performed.

Comments:

1. When specifying a routing sequence to be used for the shipment movement in lieu of specifying each carrier within the movement, use TD502 to identify the party responsible for defining the routing sequence, and use TD503 to identify the actual routing sequence, specified by the party identified in TD502.

Loop N9

Pos: 295	Repeat: 1000
Optional	
Loop: N9	Elements: N/A

User Option (Usage): Used

To transmit identifying information as specified by the Reference Identification Qualifier

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
295	N9	Reference Identification	O	1		Used
300	MSG	Message Text	O	1000		Used

N9 Reference Identification

Pos: 295	Max: 1
Heading - Optional	
Loop: N9	Elements: 2

User Option (Usage): Used

To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

Code Name

ZZ Mutually Defined

N902	127	Reference Identification	X	AN	1/30	Used
------	-----	--------------------------	---	----	------	------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

Code Name

NOTE Note to sales rep

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

MSG Message Text

Pos: 300	Max: 1000
Heading - Optional	
Loop: N9	Elements: 1

User Option (Usage): Used

To provide a free-form format that allows the transmission of text information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MSG01	933	Free-Form Message Text	M	AN	1/264	Must use

Description: Free-form message text

Syntax Rules:

1. C0302 - If MSG03 is present, then MSG02 is required.

Semantics:

1. MSG03 is the number of lines to advance before printing.

Comments:

1. MSG02 is not related to the specific characteristics of a printer, but identifies top of page, advance a line, etc.
2. If MSG02 is "AA - Advance the specified number of lines before print" then MSG03 is required.

Loop N1

Pos: 310	Repeat: 200
Optional	
Loop: N1	Elements: N/A

User Option (Usage): Used

To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
310	N1	Name	O	1		Used
320	N2	Additional Name Information	O	2		Used
330	N3	Address Information	O	2		Used
340	N4	Geographic Location	O	>1		Used
360	PER	Administrative Communications Contact	O	>1		Used

N1 Name

Pos: 310	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

User Option (Usage): Used

To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use
		Description: Code identifying an organizational entity, a physical location, property or an individual				
		Code Name				
		BY				Buying Party (Purchaser)
		ST				Ship To
N102	93	Name	X	AN	1/60	Used
		Description: Free-form name				
N103	66	Identification Code Qualifier	X	ID	1/2	Used
		Description: Code designating the system/method of code structure used for Identification Code (67)				
		Code Name				
		9				D-U-N-S+4, D-U-N-S Number with Four Character Suffix
		91				Assigned by Seller or Seller's Agent
N104	67	Identification Code	X	AN	2/80	Used
		Description: Code identifying a party or other code				

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N2 Additional Name Information

Pos: 320	Max: 2
Heading - Optional	
Loop: N1	Elements: 1

User Option (Usage): Used

To specify additional names or those longer than 35 characters in length

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N201	93	Name	M	AN	1/60	Must use

Description: Free-form name

N3 Address Information

Pos: 330	Max: 2
Heading - Optional	
Loop: N1	Elements: 1

User Option (Usage): Used

To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/55	Must use

Description: Address information

N4 Geographic Location

Pos: 340	Max: >1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Used
		Description: Free-form text for city name				
N402	156	State or Province Code	O	ID	2/2	Used
		Description: Code (Standard State/Province) as defined by appropriate government agency				
N403	116	Postal Code	O	ID	3/15	Used
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				

Syntax Rules:

1. C0605 - If N406 is present, then N405 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

PER Administrative Communications Contact

Pos: 360	Max: >1
Heading - Optional	
Loop: N1	Elements: 6

User Option (Usage): Used

To identify a person or office to whom administrative communications should be directed

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PER01	366	Contact Function Code	M	ID	2/2	Must use
		Description: Code identifying the major duty or responsibility of the person or group named				
		Code Name				
		BD				Buyer Name or Department
PER02	93	Name	O	AN	1/60	Used
		Description: Free-form name				
PER03	365	Communication Number Qualifier	X	ID	2/2	Used
		Description: Code identifying the type of communication number				
		Code Name				
		TE				Telephone
PER04	364	Communication Number	X	AN	1/80	Used
		Description: Complete communications number including country or area code when applicable				
PER05	365	Communication Number Qualifier	X	ID	2/2	Used
		Description: Code identifying the type of communication number				
		Code Name				
		EM				Electronic Mail
PER06	364	Communication Number	X	AN	1/80	Used
		Description: Complete communications number including country or area code when applicable				

Syntax Rules:

1. P0304 - If either PER03 or PER04 is present, then the other is required.
2. P0506 - If either PER05 or PER06 is present, then the other is required.
3. P0708 - If either PER07 or PER08 is present, then the other is required.

Loop PO1

Pos: 010	Repeat: 100000
Mandatory	
Loop: PO1	Elements: N/A

User Option (Usage): Must use

To specify basic and most frequently used line item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
010	PO1	Baseline Item Data	M	1		Must use
050		Loop PID	O		1000	Used
289	MSG	Message Text	O	>1		Used

PO1 Baseline Item Data

Pos: 010	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 9

User Option (Usage): Must use

To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	Assigned Identification	O	AN	1/20	Used
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
PO102	330	Quantity Ordered	X	R	1/15	Used
		Description: Quantity ordered				
PO103	355	Unit or Basis for Measurement Code	O	ID	2/2	Used
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		Code Name				
		EA	Each			
PO104	212	Unit Price	X	R	1/17	Used
		Description: Price per unit of product, service, commodity, etc.				
PO105	639	Basis of Unit Price Code	O	ID	2/2	Not used
		Description: Code identifying the type of unit price for an item				
		All valid standard codes are used.				
PO106	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		Code Name				
		MG	Manufacturer's Part Number			
PO107	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				
PO108	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		Code Name				
		PI	Purchaser's Item Code			
PO109	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Loop PID

Pos: 050	Repeat: 1000
Optional	
Loop: PID	Elements: N/A

User Option (Usage): Used

To describe a product or process in coded or free-form format

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
050	PID	Product/Item Description	O	1		Used

PID Product/Item Description

Pos: 050	Max: 1
Detail - Optional	
Loop: PID	Elements: 5

User Option (Usage): Used

To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID01	349	Item Description Type	M	ID	1/1	Must use
		Description: Code indicating the format of a description				
		Code Name				
		F Free-form				
PID02	750	Product/Process Characteristic Code	O	ID	2/3	Not used
		Description: Code identifying the general class of a product or process characteristic All valid standard codes are used.				
PID03	559	Agency Qualifier Code	X	ID	2/2	Not used
		Description: Code identifying the agency assigning the code values All valid standard codes are used.				
PID04	751	Product Description Code	X	AN	1/12	Not used
		Description: A code from an industry code list which provides specific data about a product characteristic				
PID05	352	Description	X	AN	1/80	Used
		Description: A free-form description to clarify the related data elements and their content				

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.

3. PID07 specifies the individual code list of the agency specified in PID03.

MSG Message Text

Pos: 289	Max: >1
Detail - Optional	
Loop: PO1	Elements: 1

User Option (Usage): Used

To provide a free-form format that allows the transmission of text information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MSG01	933	Free-Form Message Text	M	AN	1/264	Must use

Description: Free-form message text

Syntax Rules:

1. C0302 - If MSG03 is present, then MSG02 is required.

Semantics:

1. MSG03 is the number of lines to advance before printing.

Comments:

1. MSG02 is not related to the specific characteristics of a printer, but identifies top of page, advance a line, etc.
2. If MSG02 is "AA - Advance the specified number of lines before print" then MSG03 is required.

Loop CTT

Pos: 010	Repeat: 1
Optional	
Loop: CTT	Elements: N/A

User Option (Usage): Used

To transmit a hash total for a specific element in the transaction set

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
010	CTT	Transaction Totals	O	1		Used
020	AMT	Monetary Amount	O	1		Used

CTT Transaction Totals

Pos: 010	Max: 1
Summary - Optional	
Loop: CTT	Elements: 1

User Option (Usage): Used

To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use

Description: Total number of line items in the transaction set

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

AMT Monetary Amount

Pos: 020	Max: 1
Summary - Optional	
Loop: CTT	Elements: 2

User Option (Usage): Used

To indicate the total monetary amount

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
AMT01	522	Amount Qualifier Code	M	ID	1/3	Must use
		Description: Code to qualify amount				
		<u>Code</u> <u>Name</u>				
		TT Total Transaction Amount				
AMT02	782	Monetary Amount	M	R	1/18	Must use
		Description: Monetary amount				

SE Transaction Set Trailer

Pos: 030	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	NO	1/10	Must use
Description: Total number of segments included in a transaction set including ST and SE segments						
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set						

Comments:

1. SE is the last segment of each transaction set.

GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the end of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	Number of Transaction Sets Included	M	N0	1/6	Must use
		Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element				
GE02	28	Group Control Number	M	N0	1/9	Must use
		Description: Assigned number originated and maintained by the sender				

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	Number of Included Functional Groups	M	N0	1/5	Must use
		Description: A count of the number of functional groups included in an interchange				
IEA02	I12	Interchange Control Number	M	N0	9/9	Must use
		Description: A control number assigned by the interchange sender				